



Connection Functions

At Terminal	Function
D/U D	Speech from door
D/U E	Speech to door
PSU 12	12v AC for ringing & lock
PSU 0	12v AC for ringing & lock
PSU +	12v DC for speech & lamps
PSU -	12v DC for speech & lamps
TEL A2	Ringer Warble
TEL A1	Ringer buzzer (if fitted)
TEL L	Speech from door
TEL P	Speech to door
TEL 1-4	Buttons
TEL B	Common for ringers
TEL F	Common for speech
TEL G	Common for buttons
11ARU CBP1-2	Door button feeds
11ARU D1-2	Speech from Panels
11ARU E1-2	Speech to Panels
11ARU Lock1-2	To door releases
IC7RU CBP	Common button feed
IC7RU N/O	Lock relay 'open' contact
IC7RU N/C	Lock relay 'closed' contact
IC7RU Com	Lock relay common contact

Plan 23 Provides Ringing, Communication and Door Release, to 2 entrances, with full Intercom between all phones, limited to 10 phones. Intercom Phones have twin ringers, so that they Warble when called from a door, and Buzz when called on internal intercom.
 Notes Insert LINKS everywhere shown ●●●. Ringer Warble volume, all phones have a spindle at the top left corner. Speech volume is adjustable on the back of the entrance panel. Speaker and Microphone have separate controls.

Title : WDA_23_3_204

Date : August 2017 Drawn by : TH