



Connection Functions

At	Terminal	Function
D/U	D	Speech from door
D/U	E	Speech to door
PSU	+	12v DC
PSU	-	12v DC
TEL	A2	Ringer Warble
TEL	A1	Ringer buzzer (DO NOT USE)
TEL	L	Speech from door
TEL	P	Speech to door
TEL	1-10	Intercom buttons
TEL	B	Common for ringers
TEL	F	Common for speech
TEL	G	Common for buttons

Plan 1 Provides Ringing, Communication and Door Release functions.
 Notes Insert LINKS everywhere shown ●—●. Ringer Warble volume, all phones have a spindle at the top left corner. Speech volume is adjustable on the back of the entrance panel. Speaker and Microphone have separate controls.

Title : WDA_1_3_202_DC	
Date : August 2017	Drawn by : TH
Application :	Plan 1 – Multi Button D/U for 12V DC