



Connection Functions

At	Terminal	Function
D/U	D	Speech from door
D/U	E	Speech to door
PSU	12	12v AC for ringing & lock
PSU	0	12v AC for ringing & lock
PSU	+	12v DC for speech & lamps
PSU	-	12v DC for speech & lamps
TEL	A2	Ringer Warble
TEL	A1	Ringer buzzer (if fitted)
TEL	L	Speech from door
TEL	P	Speech to door
TEL	1-3	Intercom buttons
TEL	4	Lock button
TEL	B	Common for ringers
TEL	F	Common for speech
TEL	G	Common for buttons
IC7RU	CBP	Common button feed
IC7RU	N/O	Lock relay 'open' contact
IC7RU	N/C	Lock relay 'closed' contact
IC7RU	Com	Lock relay common contact

Plan 3 Provides Ringing, Communication and Door Release, with full Intercom between all phones, limited to 10 buttons on phones. Intercom Phones have twin ringers, so that they Warble when called from a door, and Buzz when called on internal intercom.
 Notes Insert LINKS everywhere shown ●●●. Ringer Warble volume, all phones have a spindle at the top left corner. Speech volume is adjustable on the back of the entrance panel. Speaker and Microphone have separate controls.

Title : WDA_3_3_204

Date : August 2017 Drawn by : TH

Application : Plan 3 Intercom – Multi Button D/U