

~.	Cillina	Tunction
D/U	D	Speech from door
D/U	E	Speech to door
PSU	12	12v AC for ringing & lock
PSU	0	12v AC for ringing & lock
PSU	+	12v DC for speech & lamps
PSU	-	12v DC for speech & lamps
TEL	A2	Ringer Warble
TEL	A1	Ringer buzzer (if fitted)
TEL	L	Speech from door
TEL	P	Speech to door
TEL	1	Lock button
TEL	В	Common for ringers
TEL	F	Common for speech
TEL	G	Common for buttons

Plan 1 Provides Ringing, Communication and Door Release functions.

Notes Insert LINKS everywhere shown . Ringer Warble volume, all phones have a spindle at the top left corner. Speech volume is adjustable on the back of the entrance panel. Speaker and Microphone have separate controls.

Date: July 2023

Title:

Drawn by : тн

Entryphone Co. Ltd. 23 Granville Road, London, SW18 5SD U.K. T:020 8870 8635 www.entryphone.co.uk Application:

Upgrade differences

WDA_Model-Changes