



Connection Functions

At	Terminal	Function
PSU	12	12v AC for ringing
PSU	0	12v AC for ringing
PSU	+	12v DC for speech
PSU	-	12v DC for speech
TEL	A2	Ringer Warble
TEL	A1	Ringer buzzer (if fitted)
TEL	L	Speech incoming
TEL	P	Speech outgoing
TEL	1-2	Intercom buttons
TEL	B	Common for ringers
TEL	F	Common for speech
TEL	G	Common for buttons

Plan A Provides full internal intercom between all phones, limited to 10 buttons on phones.
 Notes Insert LINKS everywhere shown ●—●. Ringer Warble volume, all phones have a spindle at the top left corner.
 Intercom Phones have twin ringers, a Warble and Buzzer, choose preference.

Title : WDA_A_5_204

Date : August 2017 Drawn by : TH